

CORRELATION OF USE MARKING AND PRODUCT IDENTITY TEXT FOR NEW PRODUCT
IDENTITY TEXT FOR ULI LISTING MARKS

The Product Identity of the ULI Listing Mark for products in this file has been revised with the transition to the new Product Identity to be completed by December 31, 2008. In conjunction with the implementation of the new Listing Mark product identity covered in the following Section General Page(s) which have been added to this File, it is required that the use marking and product identity described below is employed on *each model* at the time the new Product Identities of the Listing Mark are introduced. The products are eligible to use the previous ULI Listing Mark Product Identities covered in this Section General until December 31, 2008. The Product Identity for the ULC Listing Mark remains unchanged.

Each control unit shall be marked "Residential" or "Household," the use marking indicated in the table below for the applicable complementary Listed categories, followed by the specific use indicated in the description section of the report. Where the product is comprised entirely of labeled subassemblies, the use marking is to be applied to a subassembly used exclusively for the product and employed in every installation. [The subassembly which employs all the required marking is identified in the marking portion of the description section for the product.] Use marking is not required for the remaining labeled subassemblies. With respect to Subassemblies, only the models that are referenced later in this Section General are eligible to bear the Listing Mark.

The following table correlates the new required use marking with the product identity (Listing Mark text) of the previous Type L Listing Mark. Please refer to the Type L Listing Mark section shown below this table for information to assist in the use of this table. If more than one product identity was previously applicable, the new use marking texts shall be combined (See below for examples).

CCN	Product Identity Included in Former ULI Type L label Text	New Product Identity ULI Listing Mark	New Required Use Marking
-----	---	---------------------------------------	--------------------------

NBSX	For products which are complete in their assembly and bear the following Listing Mark text [examples include keypads, end of line resistors, remote annunciator, and products to be mounted in an electrical outlet/gang box]: "Household Burglar Warning System Control Unit Accessory"	"Equipment" "Security" added to product identity when complementary Listed categories are other than security.	"Residential" or "Household"
NBSX	For products which are incomplete in their assembly and bear the following Listing Mark text [examples include printed circuit boards, enclosures, and products to be mounted inside a separate enclosure]: "Household Burglar Warning System Accessory," "Household Burglar Warning System Accessory Enclosure,"	"Subassembly" "Security" added to product identity when complementary Listed categories are other than security.	All subassemblies marked "Residential" or "Household"
UTOU	"Household Fire Warning System Control Unit," "Household Fire Warning System Control Unit for Use with Listed Modules,"	"Fire Alarm Equipment"	"Residential" or "Household" followed by the specific use indicated in the description section of the report.

<p>UTOU</p>	<p>For products which are incomplete in their assembly and bear the following Listing Mark text [examples include printed circuit boards, enclosures, and products to be mounted inside a separate enclosure]: "Household Fire Warning System Control Unit Accessory," "Household Fire Warning System Enclosure," or "Household Fire Warning System Module"</p>	<p>"Fire Alarm Subassembly"</p>	<p>"Residential" or "Household"</p>
<p>UTOU/UTOU7</p>	<p>For products which are complete in their assembly and bear the following Listing Mark text [examples include keypads, end of line resistors, remote annunciator, and products to be mounted in an electrical outlet/gang box]: "Household Fire Warning System Control Unit Accessory," or "Household Fire Warning System Module"</p>	<p>"Fire Alarm Equipment"</p>	<p>"Residential" or "Household"</p>

UOJZ	"Signal System Control Unit"	"Fire Alarm Equipment"	Each unit shall be marked "Commercial Fire," the applicable use marking indicated for the complementary Listed categories, and either "Protected Premise Control Unit" or "Supervising Station Control Unit," as covered in the description section for the unit.
UOJZ	"Signal System Control Unit Subassembly", "Signal System Control Unit Enclosure", or "Signal System Control Unit Enclosure Part"	"Fire Alarm Subassembly"	All subassemblies marked "Commercial Fire" Key subassembly use marking will include the following: "Commercial," the applicable use marking indicated for the complementary Listed categories, and either "Protected Premise Control Unit" or "Supervising Station Control Unit," as covered in the description section for the unit.
UOXX	"Signaling Device"	"Fire Alarm Equipment"	All subassemblies are marked "Commercial Fire"
UOXX	"Signaling Device Subassembly," "Signaling Device Enclosure," or "Signaling Device Enclosure Part"	"Fire Alarm Subassembly"	All subassemblies are marked "Commercial Fire"

UTOU/UTOU7 and NBSX/NBSX7	"Household Fire and Burglar Warning System Control Unit," "Household Fire and Burglar Warning System Control Unit for Use with Listed Modules,"	"Fire Alarm and Security Equipment"	"Residential" or "Household"
UTOU/UTOU7 and NBSX/NBSX7	For products which are incomplete in their assembly and bear the following Listing Mark text [examples include printed circuit boards, enclosures, and products to be mounted inside a separate enclosure]: "Household Fire and Burglar Warning System Control Unit Accessory," "Household Fire and Burglar Warning System Enclosure," or "Household Fire and Burglar Warning System Module"	"Fire Alarm and Security Subassembly"	All subassemblies marked "Residential" or "Household"
UTOU/UTOU7 and NBSX/NBSX7	For products which are complete in their assembly and bear the following Listing Mark text [examples include keypads, end of line resistors, remote annunciator, and products to be mounted in an electrical outlet/gang box]: "Household Fire and Burglar Warning System Control Unit Accessory," or "Household Fire and Burglar Warning System Module"	"Fire Alarm and Security Equipment"	
MULQ	"Home health Care Control Unit"	"Emergency Signaling Equipment"	Home health Care Signaling

MULQ	"Home health Care Control Unit Subassembly," "Home health Care Control Unit Enclosure," or "Home health Care Control Unit Enclosure Part"	"Emergency Signaling Equipment"	All subassemblies marked "Home health Care Signaling"
AMCX, AOTX, APAW	"Burglar Alarm System Control Unit"	"Equipment"	Use marking included in description section for unit.
AMCX, AOTX, APAW	"Burglar Alarm System Control Unit Subassembly" "Burglar Alarm System Control Unit Enclosure," or "Burglar Alarm System Control Unit Enclosure Part"	"Subassembly"	All subassemblies marked "Commercial Burglar" Key subassembly will include the following use marking: Use marking included in description section for unit.
ANSR	"Intrusion detection Unit"	"Equipment"	Specific use marking (i.e. motion sensor, PIR, etc.)
ANSR	"Intrusion detection Unit Enclosure"	"Subassembly"	None, except when key subassembly as noted above. Key subassembly will include the following use marking: "Specific use marking (i.e. transponder, module, etc.)"
ANET	"Hold-Up Alarm"	"Equipment"	Hold-Up Alarm
ANET	"Hold-Up Alarm Subassembly," "Hold-Up Alarm Enclosure," or "Hold-Up Alarm Enclosure Part"	"Subassembly"	All subassemblies marked "Hold-Up Alarm". Key subassembly will include the following use marking: "Hold-Up Alarm"
AMQV	Connectors and Switches: "As shown in individual Listing"	"Equipment"	"Specific use marking (i.e. connector, etc.)"

UCST	"AUDIBLE SIGNAL APPLIANCE FOR GENERAL SIGNALING (NON-FIRE ALARM) USE"	"General Signaling Equipment"	Audible Signal appliance for general signaling (Non-Fire Alarm) use.
UCST	"AUDIBLE SIGNAL APPLIANCE FOR GENERAL SIGNALING (NON-FIRE ALARM) USE SUBASSEMBLY"	"General Signaling Subassembly"	Audible Signal appliance for general signaling (Non-Fire Alarm) use subassembly.
ULSZ	"AUDIBLE SIGNALING APPLIANCE FOR FIRE ALARM SERVICE" or "AUDIBLE SIGNALING APPLIANCE FOR FIRE ALARM SERVICE - PRIVATE MODE ONLY", "AUDIBLE SIGNAL APPLIANCE ACCESSORY"	"Fire Alarm Equipment"	"Audible signaling appliance for fire alarm service," "Audible signaling appliance for fire alarm service - private mode," or "Audible signal appliance accessory" as applicable.
ULSZ	"AUDIBLE SIGNALING APPLIANCE FOR FIRE ALARM SERVICE SUBASSEMBLY"	"Fire Alarm Subassembly"	"Audible signaling appliance for fire alarm service subassembly"
AMTB	"ALSO CLASSIFIED IN ACCORDANCE WITH ANSI/SIA CP-01-2000."	"ALSO CLASSIFIED IN ACCORDANCE WITH ANSI/SIA CP-01-2000."	None

Examples of the use marking and product identity for products complying with multiple categories:

Current ULI Type L Listing Mark Product Identity	New ULI Listing Mark Product Identity	New Use Marking to be employed with new ULI Listing Mark Product Identity
HOUSEHOLD FIRE AND BURGALR WARNING SYSTEM, ALSO SUITABLE FOR USE AS A BURGLAR ALARM SYSTEM CONTROL UNIT, ALSO SUITABLE FOR USE AS A HOLD UP ALARM UNIT "ALSO CLASSIFIED IN ACCORDANCE WITH ANSI/SIA CP-01-2000."	"Fire Alarm and Security Equipment" "ALSO CLASSIFIED IN ACCORDANCE WITH ANSI/SIA CP-01-2000."	Residential, [Burglar Alarm use marking included in description section for unit], and Hold-Up Alarm, followed by [specific use indicated in the description section of the report such as control unit, keypad, etc.]

HOUSEHOLD FIRE AND BURGALR WARNING SYSTEM, ALSO SUITABLE FOR USE AS HOME HEALTH CARE CONTROL UNIT	"Fire Alarm, Security and Emergency Signaling Equipment"	Residential and Home Health Care Signaling Control Unit
HOUSEHOLD FIRE AND BURGALR WARNIGN SYSTEM SUBASSEMBLY, ALSO SUITABLE FOR USE AS HOME HEALTH CARE CONTROL UNIT SUBASSEMBLY	"Fire Alarm, Security and Emergency Signaling Subassembly"	<p>Generally: "Residential and Home Health Care Signaling"</p> <p>Key subassembly will include the following use marking: "Residential and Home Health Care Signaling followed by [specific use indicated in the description section of the report such as control unit, keypad, etc.]</p>